


# Installation instructions

## 安装说明书



Tree lighting / 照树灯

Suitable for use with similar products / 适于用同类产品

### Installation Guide / 安全指引

The appliance should be installed, connected and tested by qualified electrician, and in accordance with local regulations. 电器应由合格的电工安装、连接和测试，并符合当地法规。

Turn off the power supply before installation or maintenance of the appliance, and make sure that the cables will not be squeezed or damaged by sharp edges.

在安装或维护设备之前，请关闭电源，并确保电缆不会被锋利的边缘挤压或损坏。

Ensure that LED lighting fixtures do not come into contact with corrosive chemicals, solvents, or abrasive cleaners.

确保 LED 灯具不会接触到腐蚀性化学物质、溶剂或研磨清洁剂等。

To avoid injury or damage to the lighting fixtures, please ensure that the power cord and lighting fixtures are securely installed before connecting the power supply.

为避免受伤或损坏灯具，请在连接电源前确保电源线和灯具安装牢固。

### WARNING / 警告

LED lighting fixtures are low voltage distribution. Before connecting the 220V power supply, please ensure that the device is correctly connected to the driver. Otherwise, it will damage the equipment. After activation, hot swapping is not allowed in the drive.

LED 灯具为低压配电。在连接 220V 电源之前，请确保设备已正确连接到驱动器。否则，会损坏设备。开启后，驱动器中不允许热插拔。

Before any maintenance, adjustment, or cleaning of the lighting fixtures, always ensure that the power is turned off and the LED fixtures have cooled down. Electrical appliances can be cleaned with a soft cloth and standard pH neutral detergent.


在对灯具进行任何维护、调整或清洁之前，始终确保电源已关闭，LED 灯具已冷却。可用软布和标准 PH 中性洗涤剂清洁电器。

Electrical appliances should not be covered with insulation blankets or similar materials. Otherwise, it is easy to cause fire accidents.

电器不应被隔热毯或类似材料覆盖。否则易造成火灾故障。


1 Testing products and accessories.

检测产品及配件。




2 After determining the installation position, place the chassis on the installation surface and make drilling marks.

确定安装位后将底盘置于安装面，做好打孔标记。




3 Use appropriate expansion bolts (M6) to secure the chassis through the mounting holes.

用合适的膨胀螺栓 (M6) 通过安装孔将底盘固定。




4 Thread the power cord through the middle hole and connect it to the lighting fixture.

将电源线从中孔穿出，并与灯具连接。



# Installation instructions

## 安装说明书




Tree lighting / 照树灯

Suitable for use with similar products / 适于用同类产品

5 Connect the light fixture to the base and secure it with side screws.


将灯具与底座相连，并通过侧面螺丝锁紧。



6 Use tools to adjust the lighting fixtures to the appropriate installation position.


用工具将灯具调整到合适的安装位置。

Adjust the angle  
调节角度



7 Check the wiring and ensure that the installation of the lighting fixtures is secure. If there are no errors, power can be turned on.

检查线路，灯具安装是否牢固，无误即可通电。



### Connection / 接线方式

The power input is AC220V, DC24V, or DC48V. Select the corresponding power supply method according to the product manual. And ensure compliance with local power supply standards.

电源输入为：AC220V 或者 DC24V 或 DC48V，根据产品说明书选择对应供电方式。并保证符合当地的供电标准。

Selection of wiring method / 接线方式选择

- (1) wrapping with waterproof tape / 包防水胶布 .
- (2) waterproof joints / 防水接头 .
- (3) waterproof boxes / 防水盒 .

Please confirm the power supply method and connect the driver correctly.

请确认供电方式，正确连接驱动器。

